



TM-27 whip M6 – article No.: 6202

CB ANTENNA Radiator for TRUCKS with 6 mm ANTENNA MOUNT

DESCRIPTION

Antenna with black chromed stainless steel whip. The antenna can be mounted on existing 6 mm standard screw type antenna mount as factory installed by SCANIA and VOLVO. A fine tuning can be made by acting on the metallic rings for best SWR.

For use at other trucks which have pre-installed antenna feet you can use the following Albrecht adapters:

- M5 to M6 – Art.No. 6825
- M6 to M6 – Art.No. 6826
- M6 to M7 – Art.No. 6827

SPECIFICATIONS

- Frequency Range Tunable : 26.9...27.5 MHz
- Bandwidth @ SWR < 2 : over 700 KHz (65 channels)
- Power : 20 Watts (CW) continuous
- : 100 Watts (CW) short time
- Height (approx.) : 580 mm
- Standard Mount : M6 / suitable for 6 mm screw type

Tuning Instruction

Please start tuning with both rings in lowest possible position. Release one of the two rings slightly until both rings can be easily tuned together. Start tuning on a medium channel (e.g. CH 9 or 19) and find the best position for lowest (= best) SWR. After tuning move one of the rings towards the other to fix the position again.

